

*AHELP for CIAO 3.4***thaw**Context: [sherpa](#)*Jump to:* [Description](#) [Examples](#) [Bugs](#) [See Also](#)

Synopsis

Allows model parameter(s) to vary.

Syntax

```
sherpa> THAW <arg_1> [<arg_2> ...]
```

Description

<arg> may be:

THAW Command Arguments

Argument	Description
<sherpa_modelname>.{<paramname> <#>}	Thaws the specified model component parameter.
<modelname>.{<paramname> <#>}	Thaws the specified model component parameter.
<sherpa_modelname>	Thaws all parameters of the specified model component.
<modelname>	Thaws all parameters of the specified model component.
<sherpa_model_stack> [# [ID]]	Thaws the parameters of all model components within the specified model stack (SOURCE, BACKGROUND, PILEUP, [B]NOISE, or KERNEL). # is a dataset number (default 1); see BACKGROUND for an explanation of ID.
<model_stack>	Thaws the parameters of all model components within the user-defined model stack.

The command FREEZE is used to prohibit model parameter values from varying.

In addition, model parameters may be thawed using the equivalent command

- `sherpa> <modelname>.{<paramname>|<#>}.TYPE = THAW`

Model parameters may also be thawed using the Sherpa/S-Lang module functions `set_thawed` and `set_par`.

Example 1

Thaw a model parameter:

```
sherpa> GAUSS[modelb]
modelb.fwhm parameter value [10]
modelb.pos parameter value [0]
modelb.ampl parameter value [1]
sherpa> THAW modelb.ampl
```

The final command thaws the parameter ampl of modelb.

Example 2

Freeze a model parameter and thaw a model parameter:

```
sherpa> FREEZE modelb.3
sherpa> THAW modelb.3
```

First, the third parameter of modelb is frozen. The last command then thaws the third parameter of modelb.

Example 3

Freeze all model parameters and thaw two model parameters:

```
sherpa> FREEZE modelb
sherpa> THAW modelb.fwhm modelb.pos
```

First, all parameters of modelb are frozen. The last command then thaws the fwhm and pos parameters of modelb.

Example 4

Freeze or thaw all source component parameters at once:

```
sherpa> PARAMPROMPT OFF
Model parameter prompting is off
sherpa> POW[modelc]
sherpa> GAUSS[modelf]
sherpa> SOURCE 2 = modelc + modelf
sherpa> FREEZE SOURCE 2
sherpa> SHOW SOURCE 2
Source 2:

(modelc + modelf)
powlaw1d[modelc] (integrate: on)
  Param   Type      Value      Min      Max      Units
  -----  -----  -----
  1  gamma  frozen       1     -10       10
  2  ref    frozen  1-3.4028e+38 3.4028e+38
  3  ampl   frozen       1     1e-20  3.4028e+38
gauss1d[modelf] (integrate: on)
  Param   Type      Value      Min      Max      Units
  -----  -----  -----
  1  fwhm  frozen  10 1.1755e-38 3.4028e+38
  2  pos   frozen  0-3.4028e+38 3.4028e+38
  3  ampl   frozen  1-3.4028e+38 3.4028e+38
sherpa> THAW SOURCE 2
sherpa> SHOW SOURCE 2
(modelc + modelf)
```

powlaw1d[modelc] (integrate: on)					
Param	Type	Value	Min	Max	Units
1	gamma	thawed	1	-10	10
2	ref	frozen	1-3.4028e+38	3.4028e+38	
3	ampl	thawed	1	1e-20	3.4028e+38
gauss1d[modelf] (integrate: on)					
Param	Type	Value	Min	Max	Units
1	fwhm	thawed	10	1.1755e-38	3.4028e+38
2	pos	thawed	0-3.4028e+38	3.4028e+38	
3	ampl	thawed	1-3.4028e+38	3.4028e+38	

This example illustrates the use of FREEZE SOURCE and THAW SOURCE to freeze and thaw all source component parameters at once, respectively. Note that thawing of some model parameters (e.g., POWLAW1D.ref) is not permitted.

Example 5

Thaw a model parameter:

```
sherpa> modelb.ampl.TYPE = THAW
```

This command thaws the parameter ampl of modelb. The following commands are each equivalent:

```
sherpa> modelb.3.TYPE = THAW
sherpa> THAW modelb.ampl
sherpa> THAW modelb.3
```

Example 6

Freeze all model parameters at once and thaw all source parameters at once:

```
sherpa> PARAMPROMPT OFF
Model parameter prompting is off
sherpa> DATA data/example.pha
sherpa> GAUSS[modelc]
sherpa> SOURCE = modelb + modelc
sherpa> FREEZE modelc
sherpa> SHOW SOURCE
(modelb + modelc)
gauss1d[modelb] (integrate: on)
    Param   Type      Value      Min      Max      Units
    -----  -----  -----
    1   fwhm  frozen   2 1.1755e-38 3.4028e+38
    2   pos   frozen   0-3.4028e+38 3.4028e+38
    3   ampl  thawed  1-3.4028e+38 3.4028e+38
gauss1d[modelc] (integrate: on)
    Param   Type      Value      Min      Max      Units
    -----  -----  -----
    1   fwhm  frozen   0.7113    0.0071   71.1283
    2   pos   frozen   0.9442    0.0276   14.5494
    3   ampl  frozen   0.0001 1.0564e-06   0.0106
sherpa> THAW SOURCE
sherpa> SHOW SOURCE
(modelb + modelc)
gauss1d[modelb] (integrate: on)
    Param   Type      Value      Min      Max      Units
    -----  -----  -----
    1   fwhm  thawed  2 1.1755e-38 3.4028e+38
    2   pos   thawed  0-3.4028e+38 3.4028e+38
    3   ampl  thawed  1-3.4028e+38 3.4028e+38
gauss1d[modelc] (integrate: on)
```

Param	Type	Value	Min	Max	Units
1	fwhm	thawed	0.7113	0.0071	71.1283
2	pos	thawed	0.9442	0.0276	14.5494
3	ampl	thawed	0.0001	1.0564e-06	0.0106

Note that the command FREEZE modelc freezes all parameters of the source model component modelc, while THAW SOURCE thaws all parameters of both source model components.

Bugs

See the [Sherpa bug pages](#) online for an up-to-date listing of known bugs.

See Also

sherpa

[autoest](#), [background](#), [create](#), [create_model](#), [createparamset](#), [fit](#), [freeze](#), [get_defined_models](#),
[get_model_params](#), [get_models](#), [get_num_par](#), [get_par](#), [get_stackexpr](#), [getx](#), [gety](#), [guess](#), [instrument](#),
[integrate](#), [is_paramset](#), [jointmode](#), [kernel](#), [lineid](#), [linkparam](#), [mdl](#), [modelexpr](#), [modelstack](#),
[nestedmodel](#), [noise](#), [paramprompt](#), [paramset](#), [pileup](#), [rename](#), [run_fit](#), [set_par](#), [set_paramset](#),
[set_stackexpr](#), [source](#), [truncate](#), [unlink](#)

The Chandra X-Ray Center (CXC) is operated for NASA by the Smithsonian
 Astrophysical Observatory.
 60 Garden Street, Cambridge, MA 02138 USA.
 Smithsonian Institution, Copyright © 1998–2006. All rights reserved.

URL:
<http://cxc.harvard.edu/ciao3.4/thaw.html>
 Last modified: December 2006